

## WF-8930/50 Distribution Panel

Item	<b>Specifications</b>
Model Number	WF-8930/50
Input Voltage	120 VAC or 240 VAC
AC Service	30 A or 50 A

AC Breakers Setup 30 Amps: "Main" + 3 Breaker stabs (5 branch circuits)

50 Amps: "Main" + 6 Breaker stabs (12 branch circuits)

DC Circuits15Fuse LED IndicatorsYesDoor Assembly WindoYes

Installation

Can be used with WF-9855, 9865, and 9875 Converters

T-30 and T-57 Transfer Switches

Case Material Plastic

Colors available Brown and Black

Shipping

**Dimensions** 13.75" (W) x 9.5" (H) x 4" (D)

Weight 3.75 lbs.

## **Standards**

**Complies with FCC** 

Yes



Specifications are subject to change without notice or obligation.

www.wfcoelectronics.com